Hubei Jucro Electric CO., LTD.

ADD: 5-1-2103, No.169-5, Tiyuchang North Rd., 443000, Yichang, Hubei, P.R.CHINA. Website: www.jucro.com Email: qiumin@jucro.com

1. General

HVD85-40.5 (ZN85-40.5) is suitable for three-phase AC power system of 50Hz and 40.5kV, used to make and break the load current, overload current and fault current in industrial and mining enterprises, power plants and transformer substations, meanwhile, it is suitable for the occasion where the frequent operation is required.

2. Service conditions

- 2.1The ambient air temperature should be -15 $^{\circ}$ C ~40 $^{\circ}$ C, the daily average temperature should not exceed 35 $^{\circ}$ C.
- 2.2 Daily mean relative humidity should not exceed 95%, and the daily mean vapor pressure should not exceed 2.2kPa; the monthly mean relative humidity should not be higher than 90%, and the monthly mean vapor pressure should not exceed 1.8kPa.
- 2.3 Altitude: Not exceed 1,000m.
- 2.4 The ambient air should be free from the dust, smoke, corrosive and flammable gas, steam, salt fog, et...

Main specifications and technical parameters

Item	Unit	Parameter	
Rated voltage	kV	40.5	
Rate voltage	kV	95	
Lighting impulse withstand voltage	kV	185	Overall and
Rated frequency	Hz	50	installation
Rated current	А	1250、1600、2000	dimensions
Rated short-time withstand current	kA	25、31.5	1. Opening spring
Rated peak value withstand current	kA	63、80	2.Main shaft
Rated short-circuit duration	S	4	3.Regulating lever of
Rated short-circuit breaking current	kA	25、31.5	intermediate phase
Rated short-circuit making current	kA	63、80	4.Driving rod
Rated operation sequence		O-0.3s-CO-180s-CO	5. Driving board 2
Breaking time	ms	<80	6.Contac spring
Rated short-circuit current breaking times	times	20	7.Driving board 3
Single capacitor bank breaking current	А	630	8.Driving board 4
Back-to-Back capacitor bank breaking current	А	400	9.Driving board 1
Rated control voltage	V	AC110、220; DC110、220	10. Regulating lever of side phase
Mechanical life	times	10000	11.Rod end bearing